



8623 Staticide® Flux Remover No Clean

Powerful solvent for rosin and No Clean flux removal

Flux Remover No Clean is a powerful solvent that removes substantial baked-on flux deposits resulting from no-clean soldering applications. This super-strength cleaner penetrates rapidly into hard-to-reach areas and will evaporate quickly without leaving residues.

Use the brush applicator for the removal of heavy soils. Test product for compatibility on plastic prior to use.

Ideal for the following applications:

- Removes R, RA, RMA, and all no-clean flux residues
- Cleans flux residues from PCBs, plugs, sockets, metal housings, motors, generators, heat sinks, ship carriers, relays, contacts, solenoids, switches, surface mount devices, and pads.

Features:

- ❖ Flammable
- ❖ Test on plastics
- ❖ Non-corrosive and safe for metals
- ❖ Evaporates quickly without leaving residue
- ❖ Low odor
- ❖ Penetrates challenging-to-reach areas
- ❖ Removes encrusted dirt, grease and other contaminants
- ❖ RoHS compliant
- ❖ No CFCs, HCFCs, or 1,1,1 Trichloroethane
- ❖ VOC: CARB 59%
- ❖ Made in USA

Directions:

To clean, spray from a distance of 4-6 inches from surface. Apply cleaner from top to bottom, allowing liquid to flush away flux residues, dirt, and oil. Use extension brush for the removal of encrusted residuals. Special valve allows for 360° spraying.

For industrial use only.
Read MSDS carefully prior to use.

Material Compatibility:

ABS	Poor
Buna-N	Poor
EPDM	Good
Graphite	Good
HDPE	Good
Kynar™	Good
LDPE	Good
Lexan™	Poor
Neoprene	Fair
Noryl	Poor
Nylon™ 66	Good
Cross-linked PE	Good
Polypropylene	Good
Polystyrene	Poor
PVC	Poor
Silicone Rubber	Poor
Teflon™	Good
Viton™	Poor

Product# 8623

12 oz (340g) aerosol / 12 per case